




## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>6</sup> : <b>H01S 3/10</b>		A1	(11) International Publication Number: <b>WO 99/31773</b>
			(43) International Publication Date: 24 June 1999 (24.06.99)
(21) International Application Number: PCT/US98/26602		(74) Agent: ROSS, John, R.; Cymer, Inc., Legal Dept. - MS/3-2A, 16750 Via Del Campo Court, San Diego, CA 92127-1712 (US).	
(22) International Filing Date: 15 December 1998 (15.12.98)			
(30) Priority Data: 08/990,848 15 December 1997 (15.12.97) US 08/995,832 22 December 1997 (22.12.97) US 09/118,773 18 July 1998 (18.07.98) US		(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, US, UZ, VN, YU, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).	
(71) Applicant (for all designated States except US): CYMER, INC. [US/US]; 16750 Via Del Campo Court, San Diego, CA 92127-1712 (US).			
(72) Inventors; and (75) Inventors/Applicants (for US only): PARTLO, William, N. [US/US]; 12634 Pedriza Drive, Poway, CA 92064 (US). BIRX, Daniel, L. [US/US]; Route 2, 175D, 3300 Crismore Lane, Oakley, CA 94561 (US). NESS, Richard, M. [US/US]; 9248 Citrus View Court, San Diego, CA 92126 (US). ROTHWEIL, Daniel, A. [US/US]; 14086 Chestnut Hill Lane, San Diego, CA 92128-4333 (US). MELCHER, Paul, C. [US/US]; 11381 Fuerte Farms Road, El Cajon, CA 92020 (US). SMITH, Brett, D. [US/US]; 11767 Stoney Peak Drive #311, San Diego, CA 92128 (US).		Published With international search report.	

(54) Title: HIGH PULSE RATE PULSE POWER SYSTEM



## (57) Abstract

A high pulse rate pulse power source (20) for supplying controlled high energy electrical pulses at rates of 2000 Hz or greater. The source (20) includes a pulse generating circuit (40) including a charging capacitor (42), a solid state switch (46) and a current limiting inductor (48). Pulses generated in the pulse generating circuit (40) are compressed in at least two pulse compression circuits (60) and a step-up pulse transformer (26) increases peak voltage to at least 12,000 volts. A very fast regulated power supply (20) is provided for charging the charging capacitor (42) in less than 400 microseconds and a pulse control system (20) including a programmed processor (102) controls the charging of the charging capacitor (42) to an accuracy of less than about one percent at a rate of at least 2000 charges per second.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

## HIGH PULSE RATE PULSE POWER SYSTEM

The present invention is a continuation-in-part of U.S. Serial No. 08/990,848 filed December 15, 1997; U.S. Serial No. 08/995,832 filed December 22, 1997; and U.S. Serial No. 09/118,773 filed July 18, 1998. This invention relates to pulse power systems and in particular to high pulse rate pulse power systems for electric discharge lasers.

## BACKGROUND OF THE INVENTION

In typical gas discharge lasers a gain medium is created by an electric discharge between two elongated electrodes into a circulating gas. Very high voltages are usually required to initiate the discharge but once the discharge begins, a plasma is created which reduces the electrical resistance between the electrodes to almost zero, effectively creating what is almost a short circuit. This requires a method to limit the current once the discharge has started. A common method to deal with the two issues is to provide a "peaking" capacitor ( $C_p$ ) in parallel with the electrodes. The peaking capacitor is periodically charged with the voltage needed to initiate the discharge but with only enough electrical energy for one pulse. The almost short circuit between the electrodes created by the high voltage drains the peaking capacitor of its energy which terminates the pulse. In high pulse rate electric discharge lasers (e.g., 1000 pulses per second) a gas circulating system produces a gas flow (such as 1,000 inches/second) between the electrodes which quickly replaces the ionized gas between the electrodes resulting from each pulse with fresh gas prior to the next pulse. The next pulse is generated by another quick charge on the peaking capacitor similar to the prior one. Thus, it is the job of the pulse power system to provide on the peaking capacitor sufficient voltage and electrical energy for one pulse at a desired pulse rate, such as 1,000 times per second.

In a prior art system, the peaking capacitor is charged from a 12-20 kv DC power source using a high voltage switch to charge a charging capacitor, Co, and a high voltage switch such as a thyatron to transfer the energy on the charging capacitor to the peaking capacitor. Other prior art pulse power systems use magnetic pulse compression circuits in order to provide the needed quick repetitive high voltage, high energy charging of the peaking capacitor. Examples are described in U.S. Patent Nos. 5,448,580 and 5,313,481 which are incorporated herein by reference. These circuits normally utilize multi-stage LC networks which convert relatively long, relatively low voltage pulses into the needed very short high voltage pulses.

The prior art includes pulse power systems supplying very high voltage short pulses for industrial gas discharge lasers such as excimer lasers at pulse rates in the range of 1,000 Hz. These lasers need to operate reliably 24 hours per day for many weeks with only short down times for routine maintenance. There is a need for pulse power systems with increased reliability which can operate at pulse rates in the range of 2,000 Hz to 5,000 Hz or greater.

### SUMMARY OF THE INVENTION

The present invention provides a high pulse rate pulse power source for supplying controlled high energy electrical pulses at rates of 2000 Hz or greater. The source includes a pulse generating circuit including a charging capacitor, a solid state switch and a current limiting inductor. Pulses generated in the pulse generating circuit are compressed in at least two pulse compression circuits and a step-up pulse transformer increases peak voltage to at least 12,000 volts. A very fast regulated power supply is provided for charging the charging capacitor in less than 400 microseconds and a pulse control system, including a programmed processor, controls the charging of the charging capacitor to an accuracy of less than about one percent at a rate of at least 2000 charges per second.

A preferred embodiment of the present invention useful for providing electrical pulses for excimer lasers, provides pulses of up to 5.5 Joules per pulse at pulse rates up to 2000 Hz or greater. In this embodiment a peaking capacitor is charged with up to 5.5 Joules from zero voltage to a discharge voltage in the range of 16,000 volts in about 100 ns. This is substantially faster than prior art designs and provides significant improvements in lasing efficiency. This faster rise time is achieved using two stages of pulse compression and a 1:23 pulse transformer, with a four-sectioned straight stainless steel rod as a secondary "winding", in between the first and second stages. In this preferred embodiment pulse energy of each pulse is controlled with a feedback control system in which the energy of previous pulses are measured and the measurements are used to determine a control voltage for a charging capacitor. This charging capacitor is then charged to the control voltage using a regulated power supply. Extremely rapid precise charging is provided in which the charging capacitor is charged at the rate of about 3 volts per microsecond to a few volts in excess of the control voltage then bleed down through a bleed circuit to the control voltage.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of a preferred embodiment of the present invention.

FIG. 2 is a simplified circuit diagram of the above preferred embodiment.

FIG. 3 is a combination block diagram, circuit diagram of a high voltage power supply which is part of the above preferred embodiment.

FIG. 4 is a prospective assembly drawing of a pulse transformer used in the above preferred embodiment.

FIG. 5 is a drawing of a primary winding of a pulse transformer used in the above preferred embodiment.

FIGS. 6A, 6B and 6C are time line charts showing pulse compression using the above preferred embodiment.

FIG. 7 is a simplified circuit diagram for providing bipolar pulses.

FIGS. 8A and 8B are drawing showing two views of a saturable inductor.

5 FIGS. 9A and 9B is a circuit drawing showing a resonance power supply.

FIGS. 10A and 10B shows the mounting of a compression lead in a preferred embodiment.

### **DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS**

Preferred embodiments of the present invention can be described by reference to the drawings.

10

#### **FIRST PREFERRED EMBODIMENT**

15

A first preferred embodiment of a pulse power system for an industrial narrow-band KrF excimer laser, is shown in block diagram form in FIG. 1. A simplified combination block and circuit diagram of this preferred embodiment is shown in FIG. 2. The diagrams show a preferred embodiment built and tested by the Applicants for converting 208 volt three phase standard plant alternating current into 0.5 Joule to 6 Joule, 12 kv to 22 kv electrical pulses on a peaking capacitor of the excimer laser at pulse rates in the range of 2,000 Hz or greater. A system description is first provided below followed by a more detailed description of some of the important details of the individual modules and components of the system.

## SYSTEM DESCRIPTION

This system is manufactured in four separate modules as indicated in FIGS. 1 and 2, each of which becomes an important part of the excimer laser system and each of which can be quickly replaced in the event of a parts failure or in the course of a regular preventative maintenance program. These modules are designated by Applicants: high voltage power supply module 20, commutator module 40, compression head module 60 and laser chamber module 80.

## High Voltage Power Supply Module

High voltage power supply module 20 comprises a 300 volt rectifier 22 for converting the 208 volt three phase plant power from source 10 to 300 volt DC. Inverter 24 converts the output of rectifier 22 to high frequency 300 volt pulses in the range 100 kHz to 200 kHz. The frequency and the on period of inverter 24 are controlled by the HV power supply control board 21 in order to provide coarse regulation of the ultimate output pulse energy of the system. The output of inverter 24 is stepped up to about 1200 volts in step-up transformer 26. The output of transformer 26 is converted to 1200 volts DC by rectifier 28 which includes a standard bridge rectifier circuit 30 and a filter capacitor 32. DC electrical energy from circuit 30 charges 8.1  $\mu$ F Co charging capacitor 42 in commutator module 40 as directed by HV power supply control board 21 which controls the operation of inverter 24 as shown in FIG. 1. Set points within HV power supply control board 21 are set by laser system control board 100.

The reader should note that in this embodiment as shown in FIG. 1 that pulse energy control for the laser system is provided by power supply module 20. The electrical circuits in commutator 40 and compression head 60 merely serve to amplify and compress the electrical energy stored on charging capacitor 42 by power supply module 20. As an example of this control, FIG. 1 indicates that control board 100 has controlled the power supply to provide 700 volts to charging capacitor 42 which during the charging cycle is isolated from the down stream circuits by solid state switch 46.

### Commutator Module

Commutator module 40 comprises Co charging capacitor 42, which in this embodiment is a bank of capacitors connected in parallel to provide a total capacitance of  $8.1 \mu\text{F}$ . Voltage divider 44 provides a feedback voltage signal to the HV power supply control board 21 which is used by control board 21 to limit the charging of capacitor 42 to the voltage (called the "control voltage") which when formed into an electrical pulse and compressed and amplified in commutator 40 and compression head 60 will produce the desired discharge voltage on peaking capacitor 82 and across electrodes 83 and 84.

In this embodiment (designed to provide electrical pulses in the range of 3 Joules and 14,000 volts at a pulse rate of 2,000 pulses per second), about 250 microseconds (as indicated in FIG. 6A) are required for power supply 20 to charge the charging capacitor 42 to 700 volts. Therefore, charging capacitor 42 is fully charged and stable at the desired voltage when a signal from commutator control board 41 closes solid state switch 44 which initiates the very fast step of converting the 3 Joules of electrical energy stored on charging capacitor into a 14,000 volt discharge across electrodes 83 and 84. For this embodiment, solid state switch 46 is a IGBT switch, although other switch technologies such as SCRs, GTOs, MCTs, etc. could also be used. A 600 nH charging inductor 48 is in series with solid state switch 46 to temporarily limit the current through switch 46 while it closes to discharge the Co charging capacitor 42.

### Pulse Generation Stage

For the first stage of pulse generation 50, the charge on charging capacitor 42 is thus switched onto  $C_1$  8.5  $\mu\text{F}$  capacitor 52 in about 5  $\mu\text{s}$  as shown on FIG. 6B.

### First Stage of Compression

A saturable inductor 54 holds off the voltage on capacitor 52 and then becomes saturated allowing the transfer of charge from capacitor 52 through 1:23 step up pulse transformer 56 to  $C_{p1}$  capacitor 62 in a transfer time period of about 550 ns, as shown on FIG. 6C, for a first stage of compression 61.



The design of pulse transformer 56 is described below. Performance wise the transformer is an extremely efficient pulse transformer, transforming a 700 volt 17,500 ampere 550 ns pulse rate into a 16,100 volt, 760 ampere 550 ns pulse which is stored very temporarily on  $C_{p-1}$  capacitor bank 62 in compression head module 60.

5

### Compression Head Module

Compression head module 60 further compresses the pulse.

### Second Stage of Compression

10

An  $L_{p-1}$  saturable inductor 64 (with about 125 nH saturated inductance) holds off the voltage on 16.5 nF  $C_{p-1}$  capacitor bank 62 for approximately 550 ns then allows the charge on  $C_{p-1}$  to flow (in about 100 ns) onto 16.5 nF  $C_p$  peaking capacitor 82 located on the top of laser chamber 80 and which is electrically connected in parallel with electrodes 83 and 84. This transformation of a 550 ns long pulse into a 100 ns long pulse to charge  $C_p$  peaking capacitor 82 makes up the second stage and last of compression as indicated at 65 on FIG. 1.

15

### Laser Chamber Module

20

25

About 100 ns after the charge begins flowing onto peaking capacitor 82 mounted on top of and as a part of the laser chamber module 80, the voltage on peaking capacitor 82 has reached about 14,000 volts and discharge between the electrodes begins. The discharge lasts about 50 ns during which time lasing occurs within the resonance chamber of the excimer laser. The resonance chamber is defined by a line narrowing package 86 comprised in this example by a 3-prism beam expander, a tuning mirror and an eschelle grating and an output coupler 88 which in this example, comprises a 10 percent R mirror. The laser pulse for this laser is a narrow band 20 ns 248 nm pulse of about 10 mJ and the repetition rate is 2000 pulses per second. The pulses define a laser beam 90 and the pulses of the beam are monitored by photodiode 92.

### Control of Pulse Energy

The signal from photodiode 94 is transmitted to processor 102 in control board 100 and the processor uses this energy signal and preferably other historical pulse energy data to set the command voltage for the next and/or future pulses. In a preferred embodiment in which the laser operates in a series of short bursts (such as 100 pulse 0.5 second bursts at 2000 Hz separated by a dead time of about 0.1 second) processor 102 in control board 100 is programmed with a special algorithm which uses the most recent pulse energy signal along with the energy signal of all previous pulses in the burst along with other historical pulse profile data to select a control voltage for the subsequent pulse so as to minimized pulse-to-pulse energy variations and also to minimize burst-to-burst energy variations. This calculation is performed by processor 102 in control board 100 using this algorithm during a period of about 35  $\mu$  s. The laser pulses occurs about 5  $\mu$  s following the To firing of IGBT switch 46 shown on FIG. 6C and about 20  $\mu$  s are required to collect the laser pulse energy data. (The start of the firing of switch 46 is called To.) Thus, a new control voltage value is thus ready (as shown on FIG. 6A) about 70 microseconds after the firing of IGBT switch 46 for the previous pulse (at 2,000 Hz the firing period is 500  $\mu$ s). The features of this algorithm are described in greater detail in U.S. Patent Application Serial No. 09/034,870 which is incorporated herein by reference.

### Energy Recovery

This preferred embodiment is provided with electronic circuitry which recovers excess energy on charging capacitor 42 from the previous pulse which substantially reduces waste energy and virtually eliminates after ringing in the laser chamber 80.

This is accomplished by the energy recovery circuit 57, composed of energy recovery inductor 58 and energy recovery diode 59, the series combination of the two connected in parallel across Co charging capacitor 42. Because the impedance of the pulse power system is not exactly matched to that of the chamber and due to the fact that the chamber impedance varies several orders of magnitude during the pulse discharge, a negative going "reflection" is generated from the main pulse which propagates back towards the front end

of the pulse generating system. After the excess energy has propagated back through the compression head 60 and the commutator 40, switch 46 opens up due to the removal of the trigger signal by the controller. The energy recovery circuit 57 reverses the polarity of the reflection which has generated a negative voltage on the charging capacitor 42 through resonant free wheeling (a half cycle of ringing of the L-C circuit made up of the charging capacitor 42 and the energy recovery inductor 58) as clamped against reversal of current in inductor 58 by diode 59. The net result is that substantially all of the reflected energy from the chamber 80 is recovered from each pulse and stored on charging capacitor 42 as a positive charge ready to be utilized for the next pulse. FIG. 6 is a time line chart showing the charges on capacitor  $C_0$ ,  $C_1$ ,  $C_{p-1}$  and  $C_p$ . The chart shows the process of energy recovery on  $C_0$ .

#### Magnetic Switch Biasing

In order to completely utilize the full B-H curve swing of the magnetic materials used in the saturable inductors, a DC bias current is provided such that each inductor is reverse saturated at the time a pulse is initiated by the closing of switch 46.

In the case of the commutator saturable inductors 48 and 54, this is accomplished by providing a bias current flow of approximately 15A backwards (compared to the normal pulse current flow) through the inductors. This bias current is provided by bias current source 120 through isolation inductor  $L_{b1}$ . Actual current flow travels from the power supply through the ground connection of the commutator, through the primary winding of the pulse transformer, through saturable inductor 54, through saturable inductor 48, and through isolation inductor  $L_{b1}$  back to the bias current source 120 as indicated by arrows B1.

In the case of compression head saturable inductor, a bias current B2 of approximate 5A is provided from the second bias current source 126 through isolation inductor  $L_{b2}$ . At the compression head, the current splits and the majority B2-1 goes through saturable inductor  $L_{p-1}$  64 and back through isolation inductor  $L_{b3}$  back to the second bias current source 126. A smaller fraction of the current B2-2 travels back through the HV cable

connecting the compression head 60 and the commutator 40, through the pulse transformer secondary winding to ground, and through a biasing resistor back to the second bias current source 126. This second smaller current is used to bias the pulse transformer so that it is also reset for the pulsed operation. The amount of current which splits into each of the two legs is determined by the resistance in each path and is intentionally adjusted such that each path receives the correct amount of bias current.

### Direction of Current Flow

In this embodiment, we refer to the flow of pulse energy through the system from the plant power source 10 to the electrodes and to ground beyond electrode 84 as "forward flow" and this direction as the forward direction. When we refer to an electrical component such as a saturable inductor as being forward conducting we mean that it is biased into saturation to conduct "pulse energy" in a direction toward the electrodes. When it is reverse conducting it is biased into saturation to conduct energy in a direction away from the electrodes toward the charging capacitor. The actual direction of current flow (or electron flow) through the system depends on where you are within the system. The direction of current flow is now explained to eliminate this as a possible source of confusion.

In this preferred embodiment Co is charged with (for example) a positive 700 volts such that when switch 46 is closed current flows from capacitor 42 through inductor 48 in a direction toward C<sub>1</sub> capacitor 52 (which means that electrons are actually flowing in the reverse direction). Similarly, the current flow is from C<sub>1</sub> capacitor 52 through the primary side of pulse transformer 56 toward ground. Thus, the direction of current and pulse energy is the same from charging capacitor 42 to pulse transformer 56. As explained below under the section entitled "Pulse Transformer" current flow in both the primary loops and the secondary loop of pulse transformer 56 are both toward ground. The result is that current flow between pulse transformer 56 and the electrodes during discharge is in the direction away from the electrodes toward transformer 56. Therefore, the direction of electron flow during discharge is from ground through the secondary of pulse

transformer 56 temporarily onto  $C_{p1}$  capacitor 62 through inductor 64, temporarily onto  $C_p$  capacitor 82, through inductor 81, through electrode 84 (which is the discharge cathode) through the discharge plasma, through electrode 83 and back to ground. Thus, between pulse transformer 56, electrons flow in the same direction as the pulse energy during discharge.

Immediately following discharge currents and electron flow are reversed as explained above and special provisions have been made in this embodiment to deal with that reverse current flow as explained above in the section entitled Energy Recovery.

#### Detailed Power Supply Description

A more detailed circuit diagram of the power supply portion of the preferred embodiment is shown in FIG. 3. As indicated in FIG. 3, rectifier 22 is a 6 pulse phase controlled rectifier with a plus 150v to -150V DC output. Inverter 24 is actually three inverters 24A, 24B and 24C. Inverters 24B and 24C are turned off when the voltage on 8  $\mu$ F  $C_o$  charging capacitor 42 is 50 volts less than the command voltage and inverter 24A is turned off when the voltage on  $C_o$  42 slightly exceeds the command voltage. This procedure reduces the charge rate near the end of the charge. Step up transformers 26A, 26B and 26C are each rated at 7 kw and transform the voltage to 1200 volt AC.

Three bridge rectifier circuits 30A, 30B and 30C are shown. The HV power supply control board 21 converts a 12 bit digital command to an analog signal and compares it with a feedback signal 45 from  $C_o$  voltage monitor 44. When the feedback voltage exceeds the command voltage, inverter 24A is turned off as discussed above, Q2 switch 34 closes to dissipate stored energy within the supply, Q3 isolation switch 36 opens to prevent any additional energy leaving the supply and Q1 bleed switch 38 closes to bleed down the voltage on  $C_o$  42 until the voltage on  $C_o$  equals the command voltage. At that time Q1 opens.

### Detailed Commutator and Compression Head Description

The principal components of commutator 40 and compression head 60 are shown on FIGS. 1 and 2 and are discussed above with regard to the operation of the system. In this section, we describe details of fabrication of the commutator.

5

### Solid State Switch

Solid state switch 46 is an P/N CM 1000 HA-28H IGBT switch provided by Powerex, Inc. with offices in Youngwood, Pennsylvania.

### Inductors

10

15

20

Inductors 48, 54 and 64 are saturable inductors similar to those described in U.S. Patents 5,448,580 and 5,315,611. A top and section view of the saturable inductor 64 is shown respectively in FIGS. 8A and 8B. However, in the inductors of this embodiment, flux excluding metal pieces 301, 302, 303 and 304 are added as shown in FIG. 8B in order to reduce the leakage flux in the inductors. These flux excluding pieces substantially reduce current flow through the inductor prior to saturation and greatly improves the pulse forming performance of the inductor in the system. The current makes four loops through vertical conductors. It enters at 305 travels down a large diameter conductor in the center labeled "1" and up six smaller conductors on the circumference also labeled "1". Other loops are similarly numbered and exits at 306. There is one additional equivalent turn formed by the flux exclusion metal itself and is the third turn in a five turn inductor. This has an advantage in that the voltage of the flux exclusion metal components is held at half the full voltage allowing a reduction in the safe hold-off spacing between the flux exclusion metal parts and the metal rods of the other turns.

### Capacitors

25

Capacitor banks 42, 52 and 62 are all comprised of banks of off-the-shelf capacitors connected in parallel. These capacitors are available from suppliers such as Murata with offices in Smyrna, Georgia. Applicants preferred method of connecting the capacitors and inductors is to bolt them to positive and negative terminals on special printed circuit board

having heavy nickel coated copper leads in a manner similar to that described in U.S. Patent No. 5,448,580.

#### Pulse Transformer

Pulse transformer 56 is also similar to the pulse transformer described in U.S. Patent Nos. 5,448,580 and 5,313,481; however, the pulse transformers of the present embodiment has only a single turn in the secondary winding and 23 primary windings. A drawing of pulse transformer 56 is shown in FIG. 4. Each of the 23 primary windings comprise an aluminum spool 56A having two flanges (each with a flat edge with threaded bolt holes) which are bolted to positive and negative terminals on printed circuit board 56B as shown along the bottom edge of FIG. 4. Insulators 56C separates the positive terminal of each spool from the negative terminal of the adjacent spool. Between the flanges of the spool is a hollow cylinder 1 1/16 inches long with a 0.875 OD with a wall thickness of about 1/32 inch. The spool is wrapped with one inch wide, 0.7 mil thick Metglas™ 2605 S3A and a 0.1 mil thick mylar film until the OD of the insulated Metglas™ wrapping is 2.24 inches. A prospective view of a single wrapped spool forming one primary winding is shown in FIG. 5.

The secondary of the transformer is a single OD stainless steel rod mounted within a tight fitting insulating tube of electrical glass. The winding is in four sections as shown in FIG. 4. The stainless steel secondary shown as 56D in FIG. 4 is grounded to a ground lead on printed circuit board 56B at 56E and the high voltage terminal is shown at 56F. As indicated above, a 700 volt pulse between the + and - terminals of the primary windings will produce a minus 16,100 volt pulse at terminal 56F on the secondary side. This design provides very low leakage inductance permitting extremely fast output risetime.

#### Details of Laser Chamber Electrical Components

The Cp capacitor 82 is comprised of a bank of 28 0.59 nf capacitors mounted on top of the chamber pressure vessel. (Typically a KrF laser is operated with a lasing gas made up of 1.0% krypton, 0.1% fluorine, and the remainder neon.) The electrodes are each solid brass

bars about 28 inches long which are separated by about 0.5 to 1.0 inch. In this embodiment, the top electrode is the cathode and the bottom electrode is connected to ground as indicated in FIG. 1.

## OTHER EMBODIMENTS

5

### Reverse Polarization

10

In the system described above Co is charged with a positive voltage and the flow of electrons is into the ground electrode of the laser chamber. The circuit can be easily reversed with Co charged to a negative charging voltage of about 700 volts and the electron flow will be from the ground electrode to the high voltage electrodes. Also reverse flow of electrons across the electrode gap could be accomplished by changing the polarity of the secondary winding (i.e., the four-section stainless steel tube).

### Bipolar Operation

15

20

25

FIG. 7 shows a modification which would permit bi-polar operation of the laser. In this case, two power supplies are provided one supplying +1200 volts and the other providing -1200 volts. In addition, switch 46 is duplicated so that we have 46A and 46B. When 46A is closed the polarity of system is like that described in detail above. However, with 46A open and switch 46B closes the resulting pulse is everywhere reversed and the electron flow across the discharge gap is from the ground electrode to the high voltage electrode (in this case about +14,000 volts). In this case, the energy recovery circuit 57 is not needed. Instead (for example) Co<sub>A</sub> is charged to +700 v at To 46A will close allowing Co<sub>A</sub> to discharge through inductor 48 then it will open and 46B will close permitting the reflected energy to be recovered on Co<sub>B</sub> after recovery of the energy 46B opens. Then Co<sub>B</sub> is charged to -700 v and at the next To 46B closes allowing Co<sub>B</sub> to discharge through the circuit. The result is alternating discharge directions. This embodiment should provide for more even wear of the electrodes.



### Compression Head Mounting

This preferred embodiment of the present invention includes a compression head mounting technique shown in FIGS. 10A and 10B. FIG. 10 is a side section view of the laser system showing the location of the compressor lead module in relation to electrodes 83 and 84. This technique was designed to minimize the impedance associated with the compression lead chamber connection and at the same time facilitates quick replacement of the compression head. As shown in FIGS. 10A and 10B the ground connection is made with an approximately 28 inch long slot tab connection along the back side of the compression head as shown at 81A in FIG. 10A and 81B in FIG. 10B. The top of the slot is fitted with flexible finger stock. A preferred finger stock material is sold under the trade name Multilam®.

The high voltage connection is made between a six-inch diameter smooth bottom of saturable inductor 64 and a mating array of flexible finger stock at 89 in FIG. 10A.. As above, a preferred finger stock material is Multilam®. This arrangement permits the replacement of the compression head module for repair or preventative maintenance in about five minutes.

### Pots and Pans Housing for Saturable Inductors

In prior art pulse power systems, oil leakage from electrical components has been a problem. In this preferred embodiment, oil insulated components are limited to the saturable inductors. Furthermore, the saturable inductors as shown in FIG. 8B are housed in a pot type oil containing housing in which all seal connections are located above the oil level to substantially eliminate the possibility of oil leakage. For example, the lowest seal in inductor 64 is shown at 308 in FIG. 8B.

### RESONANT CHARGING

In a preferred embodiment of the present invention, the power supply module described for the first preferred embodiment which utilizes two rectifiers, an inverter and a transformer as shown in FIGS. 1 and 2; is replaced by an off-the-shelf power supply and

a resonance charging circuit. This latter approach provides much faster charging of the charging capacitor.

#### First Resonant Charger

An electrical circuit showing this preferred embodiment is shown in FIG 9A. In this case, a standard capacitor charging power supply 200 having a 480 VAC/40 amp input and a 1200 VDC 50 amp output is used. Such power supplies are available from suppliers such as Ecgar, Maxwell, Kaiser and Ale. This power supply continuously charges a 325 $\mu$ F capacitor 202 to the voltage level commanded by the control board 204. The control board 204 also commands IGBT switch 206 closed and open to transfer energy from capacitor 202 to capacitor 42. Inductor 208 sets up the transfer time constant in conjunction with capacitor 202 and 42. Control board 202 receives a voltage feedback 212 that is proportional to the voltage on capacitor 42 and a current feedback 214 that is proportional to the current flowing through inductor 208. From these two feedback signals control board 204 can calculate in real time the final voltage on capacitor 42 should IGBT switch 206 open at that instant of time. Therefore with a command voltage 210 fed into control board 204 a precise calculation can be made of the stored energy within capacitor 42 and inductor 208 to compare to the required charge voltage commanded 210. From this calculation, the control board 204 will determine the exact time in the charge cycle to open IGBT switch 206.

After IGBT switch 206 opens the energy stored in the magnetic field of inductor 208 will transfer to capacitor 42 through the diode path 216. The accuracy of the real time energy calculation will determine the amount of fluctuation dither that will exist on the final voltage on capacitor 42. Due to the extreme charge rate of this system, too much dither will exist to meet a desired systems regulation need of  $\pm 0.05\%$ . Therefore a bleed down circuit is included in this embodiment

Bleed down circuit 216 will be commanded closed by the control board 204 when current flowing through inductor 208 stops. The time constant of capacitor 42 and resistor 220

should be sufficiently fast to bleed down capacitor 42 to the command voltage 210 without being an appreciable amount of the total charge cycle.

### Second Resonant Charger

A second resonant charger system is shown in FIG. 9B. This circuit is similar to the one shown in FIG. 9A. The principal circuit elements are:

I1 – A three-phase power supply 300 with a constant DC current output.

C-1 – A source capacitor 302 that is an order of magnitude or more larger than the existing C0 capacitor 42.

Q1, Q2, and Q3 – Switches to control current flow for charging and maintaining a regulated voltage on C0.

D1, D2, and D3 – Provides current single direction flow.

R1, and R2 – Provides voltage feedback to the control circuitry.

R3 – Allows for rapid discharge of the voltage on C0 in the event of a small over charge.

L1 – Resonant inductor between C-1 capacitor 302 and C0 capacitor 4-2 to limit current flow and setup charge transfer timing.

Control Board 304 – Commands Q1, Q2, and Q3 open and closed based upon circuit feedback parameters.

The power supply is a fixed 700-volt power supply. The power supply is attached directly to C-1 eliminating the need for voltage feedback to the supply. When the supply is enabled it turns on and regulates a constant current output until the voltage on C-1 capacitor 302 is 700 volts, and then it turns off.

The performance of the system is independent of the voltage regulation on C-1 therefore only the most basic control loop is necessary in the power supply. Secondly the supply will be adding energy into the system whenever the voltage on C-1 falls below the 700-volt setting. This allows the power supply the entire time between laser pulse, (and even during laser pulses), to replenish energy transferred from C-1 to C0. This further reduces

the power supply peak current requirements over the pulse power system described above. As can be seen in FIG. 6A the power supply is only given a percentage of the total time between laser pulses to charge C0 to a desired voltage. The combination of requiring a supply with the most basic control loop, and minimizing the peak current rating of the supply to the average power requirements of the system reduces the power supply cost an estimated 50%. Additionally this preferred design provides vendor flexibility since constant current, fixed output voltage power supplies are readily available from multiple sources.

In order to utilize the most basic power supply available on the market, additional circuitry is added that is estimated at a small fraction of the total power supply savings. These additional components are outlined above with the exception of C0 which is a part of the commutator. An example of operation is as follows:

Prior to the need for a laser pulse the voltage on C-1 would be charged to 700 volts, switches Q1, and Q3 would be open, and Q2 would be closed. Upon command from the laser, Q1 would close and Q2 would open. At this time current would flow from C-1 to C0 through the charge inductor L1. On the control board would be a calculator that is evaluating the voltage on C0, and the current flowing in L1 relative to a command voltage set point from the laser. Q1 will open when the voltage on C0 plus the equivalent energy stored in inductor L1 equals the desired command voltage plus 100 volts. The calculation is:

$$V_f = [V_{C0s}^2 + ((L_1 * I_{L1s}^2)/C_0)]^{0.5} + 100 \quad (1)$$

Where:

$V_f$  = The voltage on C0 after Q1 opens and the current in L1 goes to zero.

$V_{C0s}$  = The voltage on C0 when Q1 opens.

$I_{L1s}$  = The current flowing through L1 when Q1 opens.

The reason for adding 100 volts to the calculation is to ensure current is still flowing in L1 at the time the voltage on C0 equals the command voltage.

After Q1 opens the energy stored in L1 starts transferring to C0 through D2 until the voltage on C0 equals the command voltage. At this time Q2 closes and current stops  
5 flowing to C0 and is directed through D3 to produce a "flywheel current loop." A window comparitor is used to control the on off switching of Q2. Should the voltage on C0 drop below the command voltage less 0.5 volts then Q2 will open and charge current held in L1 will flow to C0 until the voltage on C0 equals the command voltage plus 0.5 volts.

Should for any reason the voltage on C0 exceed the command voltage plus 0.6 volts then  
10 Q3 will closed until the voltage on C0 drops to the command voltage plus 0.6 volts. This ensures the voltage regulation has a 0.6 volt variation worst case at the time the laser pulses.

With the above circuit, and a starting charge voltage on C-1 of 700 volts, the maximum first pulse voltage on C0 will be 1400 volts. For this embodiment, the maximum  
15 operating voltage will be 1200 volts. This allows the system to hold up to 200 volts of charge in L1 for reserve. This reserve can be incrementally pulsed onto C0 as needed due to leakage losses during the time after C0 equals the command voltage and the laser discharging C0.

In the above application a complex power supply with peak current ratings exceeding the  
20 system average current ratings is replaced with one that is much less complicated. A power supply that is far less sophisticated with the average current rating equal to the peak current rating is estimated to result in a 50% savings. An additional 10% of this savings is estimated to go back into the circuit outlined above. This results in an estimated savings of 40%.

5

Persons skilled in the art will recognize that many other embodiments of the present invention are possible based on the teachings expressed in the above disclosure. Many of the parameters such as voltage and energy values could be different. For commercial excimer lasers used for lithography charging rates of at least 1000Hz are preferred but much faster rates, such as 2000Hz or as fast as 5000Hz or greater, will be desirable. Preferably the charging capacitor charging voltage will be in the range of 600 volts or greater; and the charge energy for each charge should preferably be at least 3 Joules. Therefore, the reader should determine the scope of the present invention by the appended claims and their legal equivalents.

## CLAIMS

We claim:

1. A high pulse rate pulse power source comprising:

A) a pulse generating circuit, comprising:

- 5                   1) a charging capacitor for storing a charge at voltages in excess of 600 volts,  
                  2) a solid state switch, and  
                  3) a current limiting inductor;

for generating electrical pulses with electrical energy in excess of 3

10           Joules                   and with peak voltages in excess of 600 volts;

                  B) at least two pulse compression circuits, defining a first  
compression                   circuit and a second compression circuit, each  
                                  compression circuit comprising a bank of capacitors  
                                  and a saturable inductor;

15                   C) step-up pulse transformer for increasing the peak voltage of the  
                          electrical pulses to at least 12,000 volts said pulse transformer  
                          comprising a plurality of electrically parallel primary windings  
                          and a secondary winding comprises at least one substantially  
                          straight conductor;

20                   D) a very fast regulated power supply for charging said charging  
                          capacitor with at least 3 Joules of electrical energy at voltages  
                          of at least 600 volts, in less than 400 microseconds, and

                  E) a very fast pulse control system comprising a processor for  
controlling the charging of said charging capacitor to an accuracy of  
25                   less than one percent at a rate at least 2000 charges per second.

2. A pulse power source as in Claim 1 wherein said step-up transformer  
is a part of said first compression circuit.

3. A pulse power source as in Claim 1 wherein said at least one substantially straight conductor, four straight rods electrically connected in series.

4. A pulse power source as in Claim 1 wherein said plurality of primary windings is at least 20 primary windings.

5. A pulse power source as in Claim 1 wherein said regulated power supply comprises a bleed-down circuit comprising a switch and a resistor for bleeding down to voltage on said charging capacitor to a desired control voltage.

6. A pulse power source as in Claim 1 wherein said source is a component of an electric discharge laser and furnishes electrical pulses to generate discharges between electrodes of said laser to generate laser pulses each pulse defining a pulse energy.

7. A pulse power source as in Claim 6 and further comprising a pulse energy monitor for monitoring energy of said laser pulses.

8. A pulse power source as in Claim 7 said processor for controlling the charging of said charging capacitor is programmed with an algorithm for calculating a control voltage for a pulse on the basis of pulse energy of at least one previous pulse.

9. A pulse power source as in Claim 8 wherein said at least one previous pulse comprises all the pulses in a burst of pulses.

10. A pulse power source as in Claim 9 wherein said at least one pulse also includes pulses in earlier bursts.



11. A pulse power source as in Claim 1 wherein said at least two compression circuits in two compression circuits and the capacitor in said second compression circuit is a peaking capacitor.

5 12. A pulse power source as in Claim 1 wherein said pulse generating circuit, said compression circuits, said pulse transformer and said power supply are fabricated into modules comprising components of an electric discharge laser system defining two electrodes.

13. A pulse power source as in Claim 12 wherein said laser system is an excimer laser system.

10 14. A pulse power system as in Claim 13 wherein said excimer laser system is a KrF laser system.

15 15. A pulse power system as in Claim 12 wherein said modules are air cooled.

16. A pulse power system as in Claim 12 wherein said saturable inductors are immersed transformer oil defining an oil level contained in a pot type container having at least one real function wherein said oil level is below all of said at least one seal junction.

17. A pulse power system as in Claim 1 wherein at least one of said saturable inductors comprise at least one flux excluding piece.

20 18. A pulse power system as in Claim 1 wherein said capacitor and inductors are connected electrically using copper clad printed circuit boards and bolts for connecting the capacitors and inductors to the printed circuit boards.

19. A pulse power system as in Claim 12 wherein one of said two electrodes is connected to a ground and said pulse power system provides a negative high voltage to the other of said two electrodes.

20. A pulse power system as in Claim 12 wherein one of said two electrodes is connected to a ground and said pulse power system provides a positive high voltage to the other of said two electrodes.

21. A pulse power system as in Claim 12 wherein said pulse generating circuit is a first pulse generating circuit for generating negative pulses and further comprising a second pulse generating circuit for generating positive pulses, wherein said first pulse generating circuit and said second pulse generating circuit are controlled to produce alternating pulses to produce bipolar operation of the electric discharge laser.

22. A pulse power system as in Claim 13 wherein said excimer laser system is an ArF laser system.

23. A high pulse rate pulse power source as in Claim 1 wherein said very fast power supply comprises a power supply resonance circuit comprising:

- A) a source capacitor having a capacitance at least five times said charging capacitor capacitance;
- B) a DC power supply rated at at least 7kW for supplying electric power at at least 300 volts to said source capacitor;
- C) a current limiting power supply inductor for limiting current flow from said source capacitor to said charging capacitor;
- D) a solid state switch connected in series with said source capacitor, said current limiting power supply inductor and said charging capacitor

wherein said charging capacitor is charged by closing said solid state switch.

24. A high pulse rate pulse power source as in Claim 23 wherein said power supply resonance circuit also comprises a bleed down circuit for bleeding the voltage on said charging capacitor down to a predetermined desired value.

5 25. A high pulse rate pulse power source as in Claim 23 wherein said power supply resonance circuit further comprises flywheel current loop comprising said current limiting power supply inductor, a diode and a solid state fly wheel current loop.

10 26. A high pulse rate pulse power source as in Claim 25 wherein said processor is programmed to close said fly wheel current loop switch when voltage on said charging capacitor rises to a first predetermined value.

27. A high pulse rate pulse power source as in Claim 26 wherein said processor is further programmed to open said flywheel current loop switch when voltage on said charging capacitor decreases to a second predetermined value.




FIG.1




FIG.2




FIG.3




FIG. 4






FIG. 5








FIG.6C




FIG. 7




FIG. 8A




FIG. 8B




FIG. 9A

11 / 12




FIG. 9B




FIG. 10A




FIG. 10B

**A. CLASSIFICATION OF SUBJECT MATTER**

IPC(6) :IPC(6) HO1S 3/10

US CL :372/25, 38, 69

According to International Patent Classification (IPC) or to both national classification and IPC

**B. FIELDS SEARCHED**

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 372/25, 38, 69

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

NONE

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

NONE

**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5,313,481 A (COOK ET AL) 17 MAY 1994, (17/05/94) SEE ENTIRE DOCUMENT	1-14
A	US 5,448,580 A (BIRX ET AL) 05 SEPTEMBER 1995 (05/09/95) SEE ENTIRE DOCUMENT	1-14



Further documents are listed in the continuation of Box C.



See patent family annex.

## \* Special categories of cited documents:

- \*A\* document defining the general state of the art which is not considered to be of particular relevance
- \*E\* earlier document published on or after the international filing date
- \*L\* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- \*O\* document referring to an oral disclosure, use, exhibition or other means
- \*P\* document published prior to the international filing date but later than the priority date claimed

## \*T\*

later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

## \*X\*

document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

## \*Y\*

document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

## \*Z\*

document member of the same patent family

Date of the actual completion of the international search

10 FEBRUARY 1999

Date of mailing of the international search report

17 FEB 1999

Name and mailing address of the ISA/US  
Commissioner of Patents and Trademarks  
Box PCT  
Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

LEON SCOTTLIR

Telephone No. (703) 308-4884